



## How to Setup Customer Display with DolphinPOS APP? (Customer Display)


June-02-2020, Version V1.0

Contact information: [support@dolphinpos.com](mailto:support@dolphinpos.com)

Index	Page#
Customer Display Setup with DolphinPOS APP	2-6


## Customer Setup

**Step 1:** For this Setup you need two devices (one for Teller/Cashier display and other for Customer display).




**Step 2:** And make sure Both the IPADs are connected to same **WIFI** network.

**Step 3:** On Customer display IPAD, go to IOS "Settings "→WIFI → Tap on Network to which it is connected. And note down the "IP address"




## Customer Display Setup with DolphinPOS APP

- Open DolphinPOS APP, login with the user credentials and
- go to " More " → " Setup " → " UDP Config ."
- Configure:
  - IP Address: copy from above step3
  - Port No:13000 (always Fixed)




- **Step 4:** go to " More " → " Setup " → " General " And Enable flags "is service server" and "enable customer display".



## Customer Display Setup with DolphinPOS APP

### **Step 5:** In the **Teller /cashier** IPAD


- Open DolphinPOS APP, login with the user credentials and
- Go to” More” → “Setup” → “UDP Config.”
- Configure:
  - IP Address: copy from above step3 (of customer display)
  - Port No:13000 (always Fixed)



### **Step 6:** go to” More” → “Setup” → “General” And

Enable flags “is service **client**” and “enable customer display”.


## Customer Display Setup with DolphinPOS APP



**Step 7:** Now **Close** the DolphinPOS App on both the IPADs. First turn ON Teller/cashier IPAD and then turn ON customer display IPAD.

On Teller/cashier IPAD: Go to register/sale screen

On customer display IPAD: Go to "More" → "Display screen"



## Customer Display Setup with DolphinPOS APP

**Step 7:** Once you start adding items in Teller/cashier IPAD, and then should see same items getting displayed on customer display IPAD.

Now you are good to go!!

